

ROP-111/EU

CONVENTIONAL MANUAL CALL POINT FOR OUTDOOR USE

The **ROP-111** call point is used to manually trigger an alarm when a fire is discovered. The call point is designed to work with the **CSP-104**, **CSP-108**, **CSP-204** and **CSP-208** fire alarm control panels.

- resettable plastic pane
- key to enable:
 - testing
 - resetting

LED to indicate activation of the call point

mounting box included

ROP-FLAP – optional protective cover to prevent unintentional activation

TECHNICAL DATA

Operating temperature range	-25°C...+70°C
Weight	180 g
Maximum humidity	95%
Current draw when detecting	0 mA
Current draw when emitting an alarm	25 mA
IP rating	IP66
Power supply voltage	9...30 V DC
Dimensions without holders	87 x 87 x 53 mm
Dimensions with holders	117 x 87 x 53 mm