

# SPP-110-W

## CONVENTIONAL FIRE ALARM SOUNDER

The **SPP-110** sounder is used for acoustic alarm signaling. The sounder is designed to work with the SATEL fire alarm control panels (conventional: **CSP-104**, **CSP-108**, **CSP-204**, **CSP-208**; addressable: **ACSP-402**).

- acoustic signaling by means of piezoelectric transducer
- 32 selectable tones
- selectable volume level
- available in red (**SPP-110**) and white (**SPP-110-W**)



## TECHNICAL DATA

|                                     |                   |
|-------------------------------------|-------------------|
| Operating temperature range         | -10°C...+55°C     |
| Weight                              | 225 g             |
| Maximum humidity                    | 95%               |
| Dimensions                          | 108 x 108 x 87 mm |
| Current draw when emitting an alarm | 15 mA             |
| IP rating                           | IP21C             |
| Power supply voltage                | 18...28 V DC      |
| Operating environment               | A                 |